

NEKO / FUSION / FX4  
Fixed LED Downlight



Black Reflector



Black Reflector



Specular Reflector



Specular Reflector

LED Power	System Power	LED Voltage	LED Current	CRI	CCT	Beam	LED Output	System Output	Code						
9 W	11 W	12 V	700 mA	80	2700K	24°	850lm	670lm	FX4-8272409N-WB						
						40°	850lm	670lm	FX4-8274009N-WB						
						3000K	24°	900lm	700lm	FX4-8302409N-WB					
							40°	900lm	700lm	FX4-8304009N-WB					
						4000K	24°	1000lm	750lm	FX4-8402409N-WB					
							40°	1000lm	750lm	FX4-8404009N-WB					
						9 W	11 W	12 V	700 mA	80	2700K	24°	850lm	670lm	FX4-8272409N-BB
												40°	850lm	670lm	FX4-8274009N-BB
3000K	24°	900lm	700lm	FX4-8302409N-BB											
	40°	900lm	700lm	FX4-8304009N-BB											
4000K	24°	1000lm	750lm	FX4-8402409N-BB											
	40°	1000lm	750lm	FX4-8404009N-BB											
9 W	11 W	12 V	700 mA	80	2700K							24°	850lm	700lm	FX4-8272409N-WS
												40°	850lm	700lm	FX4-8274009N-WS
						3000K	24°	900lm	750lm	FX4-8302409N-WS					
							40°	900lm	750lm	FX4-8304009N-WS					
						4000K	24°	1000lm	800lm	FX4-8402409N-WS					
							40°	1000lm	800lm	FX4-8404009N-WS					
						9 W	11 W	12 V	700 mA	80	2700K	24°	850lm	700lm	FX4-8272409N-BS
												40°	850lm	700lm	FX4-8274009N-BS
3000K	24°	900lm	750lm	FX4-8302409N-BS											
	40°	900lm	750lm	FX4-8304009N-BS											
4000K	24°	1000lm	800lm	FX4-8402409N-BS											
	40°	1000lm	800lm	FX4-8404009N-BS											

Code Remark: N=(NO Driver) F=(ON-OFF) P=(Phase Dim) A=(1-10V Dim) D=(DALI Dim)

Project: Office Helsinki, Finland

